


Manual Step Attenuator

- ◆ DC to 5.8GHz
- ◆ 0 to 35dB in 1dB Step
- ◆ 5 Watt
- ◆ Connector Type: SMA,N,TNC,F,BNC etc. available
- ◆ Low PIM



Features

- Using advanced microstrip technology, ultra-small size
- Attenuation values are adjustable in a power-on state, no sudden big reflection.
It adopts an innovative technology, and thus it eliminates sudden big reflection in attenuators when attenuation is being adjusted, preventing the preliminary RF circuit from being burnt, and keeping the system stable
- Step values: 1dB, 2dB, 4dB, 8dB,10dB,10dB
- 36 attenuation values
- High attenuation accuracy, low insertion loss
- High adjustment accuracy
- Low cost – High Performance
- Adjusting the transmitting (receiving) distance of RF signal precisely. Adjusting accuracy is limited to 5cm.
- Switch repeatability avg.> 10000 operations (5000 cycles) per switch.
- PC(Polycarbonate) Switch, operating temperature of 120°C is available.
- Attenuation values are adjustable in a power-on state, test data can be read continuously, no interruption.



Specifications

Frequency Range	DC to 5.8GHz
Attenuation	0 to 35dB
Step Value	1dB
Insertion loss at 0dB (typ.)	
	1.4dB DC to 4 GHz
	2.0dB 4 to 5 GHz
	2.5dB 5 to 5.8 GHz


Attenuation Accuracy (typ.)

-1 dB~+3.5dB	DC to 4 GHz
+5.5 dB	4 to 5 GHz
+7.0dB	5 to 5.8 GHz

Nominal Impedance	50 Ohm
Average Power	5 Watt
Operating Temperature	-40°C to +85°C

Characteristic

For example the testing curves of VAS073501T52 of 35dB



Freq. Range (GHz)	VSWR(:1)	
	Typ.	Max.
DC to 4	1.25	1.55
4 to 5.8	1.35	1.65

3rd Order Intermodulation

Two Input Signals	Reflected IM3
925MHz & 960MHz	-115dBc @ 2x37dBm
1805MHz & 1880MHz	-115dBc @ 2x37dBm
2620MHz & 2695MHz	-115dBc @ 2x37dBm

Model No. Description

VAS ** ** ** * * *
 Type Attenuation Range Step Value Connector Type Max. Power Connector Option

VAS: Step Variable Attenuator

Type: 07 represents type number

Attenuation Range: Maximum attenuation.

Connector Type: S and N and T available. S is SMA and N is N type connector and T is TNC.

Max. Power: 2 and 5 are available, currently 2W and 5W are available.


Connector Options:

Options	IO
1	Female/Female
2	Male/Female
3	Male/Male

Connector Position: "A" represents back connectors, without "A" represents left and right connectors.

Package Outlines

TNC Connector Unit: mm(inch)



Package type: T51

NOTE:

1. ALL dimensions shown in mm(tolerance: +/-0.2mm) unless stated otherwise
2. RoHS Compliant in accordance with EU Directive(2011/65/EU)

Yantel Corporation

Add: 3F, Building 3, Southern District 2 of ZhongGuan Honghualing Industrial Park, Xili, Nanshan, Shenzhen, China
 Tel: 86-755-8355-1886 Fax: 86-755-8355-2533


Attention


It is much easier to adjust the switch by tools like plastic screw driver.


Mounting Instructions: Unit: mm(inch)

This product is panel-mountable via screws.

- Four mounting holes on the product plate. Refer to Fig2, Fig6.
- H represents the thickness of panel. Refer to Fig3, Fig4.
- Recommended length of the screw is 3mm+H. Refer to Fig5.




Front View Fig 2




Lateral View Fig 3

Yantel Corporation


Add: 3F, Building 3, Southern District 2 of ZhongGuan Honghualing Industrial Park, Xili, Nanshan, Shenzhen, China
 Tel: 86-755-8355-1886 Fax: 86-755-8355-2533



Sectional View Fig 4



Recommended length of the screw Fig 5



Mounting holes on user's panel Fig 6

Note:

Attempt to disassemble the product can damage it and void your warranty. In case of any malfunction, please contact your local representative, distributor or the factory immediately.