

VAS063501F2* Miniature Variable Attenuator

International invention patent

Manual Step Attenuator

- DC to 3GHz
- 0 to 35dB in 1dB Step
- 2 Watt
- Connector Type:SMA,N,TNC,F,BNC etc. available.

Features

- Using advanced microstrip technology, ultra-small size
- Attenuation values are adjustable in a power-on state, no sudden big reflection.

It adopts an innovative technology, and thus it eliminates sudden big reflection in attenuators when attenuation is being adjusted, preventing the preliminary RF circuit from being burnt, and keeping the system stable

- Stepvalues:1dB,2dB,4dB,8dB,10dB,10dB
- 36 attenuation values
- High attenuation accuracy, low insertion loss.
- High adjustment accuracy
- Low cost High Performance
- Adjusting the transmitting (receiving) distance of RF signal precisely. Adjusting accuracy is limited to 5cm.
- Switch repeatability avg.> 10000 operations (5000 cycles) per switch.
- PC(Polycarbonate) Switch, operating temperature of 120°C is available.
- Attenuation values are adjustable in a power-on state, test data can be read continuously, no interruption.

Characteristic

For example the testing curves of VAS063501F21 of 35dB





RoHS

Specifications

Frequency Range	DC to 3GHz			
Attenuation	0 to 35dB			
Step Value	1dB			
Insertion loss at 0dB(typ.)				
	2.5dB at 3GHz			
Attenuation Accuracy(typ.)				
	0 to +1.0dB at 1GHz			
	0 to +2.0dB at 2GHz			
	0 to +3.0dB at 3GHz			
Nominal Impedance	75 Ohm			
Average Power	2 Watt			
Operating Temperature	-40℃ to +85℃			

FREQ. RANGE (GHz)	Typical	Maximum	
FREQ. RAINGE (GHZ)	SWR(:1)	SWR(:1)	
DC to 3	1.45	1.65	



A1.0

 Yantel Corporation

 Add: 3F, Building 3, Southern District 2 of Zhongguan Honghualing Industrial Park, Xili, Nanshan, Shenzhen, China

 Tel:
 86-755-8355-1886

 Fax:
 86-755-8355-2533

For detailed performance specs & shopping online see Yantel web site : <u>www.yantel-corp.com</u>



VAS063501F2* Miniature Variable Attenuator

International invention patent

Model No. Description									
VAS	**	**	**	*	*	*			
	Туре	Attenuation Range	Step Value	Connector Type	Max. Power	Connector Option			
VAS: Step Variable Attenuator									
Type: 06 represents type number									
Attenuation Range: Maximum attenuation.									
Connector Type: S and N available. S is SMA and N is N type connector.									
Max. Power: 2 and 5 are available, currently 2W and 5W are available.									
Connector Options:									
Options	IO	1							
1	Fe	emale/Female							
2	Ma	ale/Female							
3	Ma	ale/Male							

Package Outlines

F Connector



NOTE :

A1.0

- 1. ALL dimensions shown in mm(tolerance: $\pm -0.2mm$) unless stated otherwise
- 2. RoHS Compliant in accordance with EU Directive(2011/65/EU)